


Galaxy® AF-3500, 3550, GP3, GP4, & SS Display Installation Quick Guide

Complete these steps in order during the installation process. Refer to the display manual for additional information.

Step 1: Display Mounting

1. Lift the display into position on the support structure.



2. Weld or use 1/2" hardened bolts to secure all clip angles to support structure




3. Remove crane support from the display.
4. Remove all eyebolts if desired. Seal all of the remaining holes with silicone approved for use on aluminum.



5. Make sure display structure or shrouding does not block display ventilation.

Step 2: Connecting Power

1. Refer to the label on back of the display or to the display riser drawing for power requirements. Displays require either 120 VAC (2 wire + ground) or 120/240 (3 wire + ground).




2. Wire Line 1, Line 2, neutral, and ground wires according to the shop drawing.
3. Connect grounding electrode to ground lug on each display face.
4. Test the display ground to ensure it has a resistance-to-ground of 10 ohms or less.



Step 3: Communications Installation

1. Connect the signal cables to the proper Quick-Connect Jacks on the back of the display.
2. Install quick-connect cable between Primary display (J-34) and Mirror display (J-32) when applicable.
Note: Remove whiteplugs from the quick-connect cable before plugging it into the jack.



Step 4: Turn Display On


1. Turn on power to the display.
2. Observe boot sequence shown on the display to get the IP Address or DHCP name. The boot time lasts about three minutes.

Step 5: Venus 1500 Software Configuration


Refer to the Venus 1500 Help File for additional information.

1. Click **Start > All Programs > Daktronics > Venus 1500 V4** to verify Venus 1500 is installed on the control computer.
2. Click **Application button > Configure > Displays** to launch the display configuration wizard in Venus 1500.

3. Click **Add Display**.



4. Select the customer's display from the list and click **Continue**.



5. Enter the customer's password on the **Authentication Page**. **Note:** The default password for GP4 displays is **DakPassword!**
6. Click **Continue** if prompted.
7. Name the display. Click **Continue**.
8. Select the correct time zone for the display's location.
9. Click **Finish** in the Summary window. The new display appears in the Display Management window.
10. Close the **Display Management** window to return to the **Home** tab view.